



RF Solution offer a wide selection of Waveguide Circulator for global customers. BH4853-WR90 is a Waveguide Circulator in Frequency Range of 8.0~12.4 GHz. It is made of high quality materials under a high standard, the Bandwidth Max of this product is 20%, Insertion Loss Max is 0.25 dB and Isolation Min is 23.0 dB. The component has a good working performance and stability, it is ideal for handling a Forward Power of /.

### Product Details

Part Number	BH4853-WR90
Description	8.0 to 12.4 GHz Waveguide Circulator

### General Parameters

Frequency Range	8.0~12.4 GHz
Bandwidth Max	20%
Insertion Loss Max	0.25 dB
Isolation Min	23.0 dB
Forward Power	/
VSWR Max	1.15
Impedance	50 Ω
Connector Type	WR90
Size	53*48*42 mm
Weight	/
Operating Temperature	-40~+80 °C
Storage Temperature	/
ROHS Compliant	Yes

### Outline Drawing (mm)

