



RF Solution offer a wide selection of Waveguide Circulator for global customers. BH6880-WR137 is a Waveguide Circulator in Frequency Range of 5.4~8.0 GHz. It is made of high quality materials under a high standard, the Bandwidth Max of this product is 20%, Insertion Loss Max is 0.25 dB and Isolation Min is 25.0 dB. The component has a good working performance and stability, it is ideal for handling a Forward Power of /.

Product Details

Part Number	BH6880-WR137
Description	5.4 to 8.0 GHz Waveguide Circulator

General Parameters

Frequency Range	5.4~8.0 GHz
Bandwidth Max	20%
Insertion Loss Max	0.25 dB
Isolation Min	25.0 dB
Forward Power	/
VSWR Max	1.12
Impedance	50 Ω
Connector Type	WR137
Size	80*68.3*49.2 mm
Weight	/
Operating Temperature	-40~+70 °C
Storage Temperature	/
ROHS Compliant	Yes

Outline Drawing (mm)

