



RF Solution offer a wide selection of Coaxial Mismatch Termination for global customers. MT-50WXX-F6080-NJ-XXG is a Coaxial Mismatch Termination in Frequency Range of $F_0 \pm 5\%$ (F_0 is the center frequency). It is made of high quality materials under a high standard, the VSWR Max of this product is 1.50~4.00, VSWR Tolerance is $\pm 5\%$ and Impedance is 50 Ω . The component has a good working performance and stability, it is ideal for handling a Power of 50 W.

Product Details

Part Number	MT-50WXX-F6080-NJ-XXG
Description	F0±5% Coaxial Mismatch Termination

General Parameters

Frequency Range	$F_0 \pm 5\%$ (F_0 is the center frequency)
VSWR Max	1.50~4.00
VSWR Tolerance	$\pm 5\%$
Impedance	50 Ω
Power	50 W
Connector Type	N-M (J)
Size	60.0*60.0*80.0 mm
Weight	/
Operating Temperature	-55~+125 °C
Storage Temperature	/
ROHS Compliant	Yes

Outline Drawing (mm)

