



RF Solution offer a wide selection of 2 Ways Power Divider for global customers. PD02-F3034-S-2-6GHz is a 2 Ways Power Divider in Frequency Range of 2.0~6.0 GHz. It is made of high quality materials under a high standard, the Insertion Loss Max of this product is 0.5 dB, Isolation Min is 20 dB and Amplitude Unbalance is  $\pm 0.3$  dB. The component has a good working performance and stability, it is ideal for handling a Forward Power of 30 W.

### Product Details

Part Number	PD02-F3034-S-2-6GHz
Description	2.0~6.0 GHz 2 Ways Power Divider

### General Parameters

Frequency Range	2.0~6.0 GHz
Insertion Loss Max	0.5 dB
Isolation Min	20 dB
Amplitude Unbalance	$\pm 0.3$ dB
Forward Power	30 W
Reverse Power	1 W
VSWR Input Max	1.30
VSWR Output Max	1.20
Phase Unbalance	$\pm 3^\circ$
Impedance	50 $\Omega$
Connector Type	SMA-F
Size	30*34*10 mm
Weight	/
Surface Finishing	Grey Painting



Operating Temperature	-45~+85 °C
ROHS Compliant	Yes

### Outline Drawing (mm)

