



RF Solution offer a wide selection of 2 Ways Power Divider for global customers. PD02-F3634-N-2000-8000MHz is a 2 Ways Power Divider in Frequency Range of 2000~8000 MHz. It is made of high quality materials under a high standard, the Split Loss of this product is 3.0 dB, Insertion Loss Max is 0.6 dB and Isolation Min is 18.0 dB. The component has a good working performance and stability, it is ideal for handling a Forward Power of 20 W.

Product Details

Part Number	PD02-F3634-N-2000-8000MHz
Description	2000~8000 MHz 2 Ways Power Divider

General Parameters

Frequency Range	2000~8000 MHz
Split Loss	3.0 dB
Insertion Loss Max	0.6 dB
Isolation Min	18.0 dB
Forward Power	20 W
Reverse Power	2 W
VSWR Input Max	1.30
VSWR Output Max	1.25
Amplitude Balance	±0.4 dB
Phase Balance Max	±5°
Impedance	50 Ω
Connector Type	SMA-F
Size	36*34*12 mm
Weight	/



Surface Finishing	Black Painting
Operating Temperature	-45~+75 °C
ROHS Compliant	Yes

Outline Drawing (mm)

