



RF Solution offer a wide selection of 6 Ways Power Divider for global customers. PD06-F7650-S-6-18GHz is a 6 Ways Power Divider in Frequency Range of 6.0~18.0 GHz. It is made of high quality materials under a high standard, the Insertion Loss Max of this product is 1.8 dB, Isolation Min is 18 dB and Amplitude Unbalance is ± 0.8 dB. The component has a good working performance and stability, it is ideal for handling a Forward Power of 20 W.

Product Details

Part Number	PD06-F7650-S-6-18GHz
Description	6.0~18.0 GHz 6 Ways Power Divider

General Parameters

Frequency Range	6.0~18.0 GHz
Insertion Loss Max	1.8 dB
Isolation Min	18 dB
Amplitude Unbalance	± 0.8 dB
Forward Power	20 W
Reverse Power	1 W
VSWR Input Max	1.80
VSWR Output Max	1.50
Phase Unbalance	$\pm 10^\circ$
Impedance	50 Ω
Connector Type	SMA-F
Size	75.5*50*10 mm
Weight	/
Surface Finishing	Grey Painting



Operating Temperature	-45~+85 °C
ROHS Compliant	Yes

Outline Drawing (mm)

